



MonkeyLabs
Creative Connected Gadgets
www.monkeylabs.in



Smart Security Automator

Proudly Made in INDIA

3Alarm Smart Security System



Connected Intrusion/Motion Security System

Remote Mobile Roaming Alarm & Auto Trigger

ARM/DisArm & MONITOR on the GO



ALARM



PHONE NOTIFICATION



ACTIVATE A PLUG

(POWER BACKUP Option Available)

Corporate : +91 8919533848 :: Partner #



MonkeyLabs
Creative Connected Gadgets



Smart Security Automator

Proudly Made in INDIA

3Alarm Intrusion/Motion Detector

Specifications

Product	3Alarm Connected Intrusion System	Country of Origin : INDIA
Code	SSSnnnnnn	
Model #	MLSSSMPIR3A	
Voltage Rating	5V 500 mA	
Detect Type	Passive Infra Red	
Connect	5V Micro USB Adaptor	
Appliance Power	500 mA	
Detection Distance Range	3 to 7 Meter	
Detection Cone	100 Degrees Motion Cone	
Mobile App	Pitaraa Home Automator	
Wi-Fi	2.4 Ghz Home Wi-Fi Router	
Packaging	Outdoor IP55 Box	
Dimensions	L . W . H : 7 x 5.5 x 2.5 C M	
Home Automator SmartApp	Secure * ARM/DisARM * Roaming * Phone Notification * Play Store * OTA * Trigger Security Lights	



Connect USB Adaptor Connector



Configuration Steps

1. **Make Note of "Serial No."**
2. Connect Power Adaptor
3. Turn On AC Mains to Adaptor
4. See Red led Glowing
5. See Blue LED Blinking
6. Blue Led Steady Glow (no Blink)
7. On Smart Phone Start App
8. Connect Smart Phone to Home Wi-Fi
9. Go to Settings in App
10. Add SSS (Wait for Secure connection)
11. Enter Yor Home Wi-Fi "Password"
12. Click " CONFIRM"
13. Select SSS device or "FIND SSS Devices"
14. Select Switch with "Serial No."
15. Enter Name of your choice
16. Click "CONNECT"
17. Wait for Blue led to Toggle/Beeps
18. Wait for Beeps
19. ONLY THEN
20. Select "OK"
21. Wait till App get back to Menu
22. Go to Main Menu
23. Select SSS
24. Check Phone Wi-Fi is connected
25. Operate SSS Device
26. ARM SSS Device



Powered by
TINGSS™

